

What is claimed is:

1. An apparatus comprising:

a central unit transmitter having an input to receive downstream digital data, and having an input for receiving a master clock signal and an input for receiving a master carrier signal, said transmitter transmitting signals from which said master clock and master carrier signals can be recovered and from which said downstream data can be recovered;

a transmission media coupled to said modulator through which signals from said central transmitter propagate;

a remote unit receiver coupled to said transmission media to receive said signals transmitted from said central unit transmitter and having a local clock reference input for receiving a local clock reference signal and a local carrier reference input for receiving a local carrier reference signal, said remote unit received for recovering and outputting said downstream data;

a tracking loop circuit in said remote unit receiver and coupled to said local clock reference input and said local carrier reference input and having a frame detector coupled to a first voltage controlled oscillator for supplying to said remote unit receiver said local clock reference signal and having a slicer coupled to a second voltage controlled oscillator for supplying said local carrier reference signal, said tracking loop circuit for locking the phase and frequency of said local clock reference signal and said local carrier reference signal to the phase and frequency of said master clock and master carrier signals from said signals transmitted by said central unit transmitter;

a remote unit transmitter coupled to said transmission media and having an input for upstream digital data and having an input coupled to receive a carrier reference signal which is phase coherent with said local master carrier reference signal and having an input coupled to receive a carrier reference signal which is phase coherent with said local clock reference signal, said remote unit transmitter, for transmitting signals from which said clock and carrier

33 reference signals can be detected and for transmitting signals from which said
34 upstream digital data can be extracted;
35
36 a central unit receiver coupled to said transmission media and having
37 inputs for receiving a phase adjusted clock signal and a phase adjusted carrier
38 signal, said central unit receiver recovering and outputting said upstream digital
39 data;

40
41 a phase detect and adjust circuit coupled to receive said master clock and
42 master carrier signals and said signals transmitted from said remote unit
43 transmitter, for supplying a phase adjusted master clock signal and a phase
44 adjusted master carrier signal to said central unit receiver, and occasionally or
45 periodically adjusting the phase of said phase adjusted master carrier signal and
46 said phase adjusted master clock signal to be phase coherent with the local
47 master carrier reference signal and the local master clock reference signal,
48 respectively, used by said remote unit transmitter to transmit said upstream
49 digital data.

1 2. A process of bidirectionally communicating digital data comprising:

2 using a master clock signal to modulate downstream digital data onto a
3 master carrier signal, and transmitting signals through a transmission media
4 from which said downstream digital data and said master clock signal and said
5 master carrier signal can be recovered;

6 receiving said signals propagating through said transmission media, and
7 recovering said master carrier and master clock signals and using said master
8 carrier and master clock signals to generate local master clock reference and
9 local master carrier reference signals which are phase coherent with said
10 recovered master clock signal and said recovered master carrier signals,
11 respectively, and using said local master clock reference and local master
12 carrier reference signals to recover said downstream digital data;

13 using said local master clock reference and local master carrier reference
14 signals to modulate upstream digital data onto said local master carrier reference
15 signal, and transmitting through said transmission media signals from which said

16 local master clock reference signal and said local master carrier reference signal
17 can be recovered and transmitting signals from which said upstream digital data
18 can be recovered;
19 receiving said signals bearing said local master clock reference and said
20 local master carrier reference signal information and bearing said upstream
21 digital data information, and receiving said master clock signal and said master
22 carrier signal and occasionally or periodically adjusting the phase or frequency
23 or both of said master clock signal and said master carrier signal so as to be
24 phase coherent with said local master clock reference signal and said local master
25 carrier reference signal, respectively, to generate a phase adjusted master clock
26 signal and a phase adjusted master carrier signal, and using said phase adjusted
27 master clock signal and said phase adjusted master carrier signal to recover said
28 upstream digital data.

1 3. A system comprising:

2
3 a central unit transceiver which uses a master clock signal and master carrier
4 signal to transmit downstream payload data;

5 a plurality of remote unit transceivers each coupled to said central unit
6 transceiver through a transmission media, and each having a receiver section including a
7 tracking loop to recover said master clock signal and a tracking loop to recovers said
8 master carrier signal from signals transmitted from said central unit transceiver, and
9 including circuitry to use said recovered master clock signal, as signals generated
10 therefrom, and said recovered master carrier signal, or signals generated therefrom, to
11 recover said downstream payload data and to transmit upstream payload data, each said
12 remote unit transceiver including circuitry to transmit preamble data preceding
13 upstream payload data for use by said central unit transceiver;

14 and wherein said central unit transceiver includes circuitry for using said
15 preamble data for determining the phase difference for the particular remote unit
16 transceiver which transmitted said preamble data between the master clock signal of the
17 central unit transceiver and that remote unit transceiver's recovered master clock
18 signal, or signals generated therefrom, and between the master carrier signal of the
19 central unit transceiver and the remote unit transceivers recovered master carrier
20 signal, or signals generated therefrom, and for using the phase difference(s) so

2 1 determined for each remote unit and a rotational amplifier and circuitry associated
2 2 therewith to get the proper phase adjustment factor for a particular remote unit applied
2 3 to said rotational amplifier when payload data from that particular remote unit
2 4 transceiver is being received so as to recover said upstream payload data transmitted by
2 5 that particular remote unit transceiver thereby eliminating the need for tracking loops
2 6 in said central unit transceiver to continuously track the clock and carrier signals used
2 7 by each said remote unit transceiver to transmit upstream payload data.

1 4. A process comprising:
2 transmitting downstream payload data from a central unit modem using a master
3 clock and master carrier;
4 recovering said master clock and master carrier signals in each of a plurality of
5 remote unit modems physically spread throughout a distributed system and using said
6 recovered master clock and master carrier or signals generated therefrom and phase
7 coherent therewith to recover downstream data in each remote unit modem, and using
8 said recovered master clock and master carrier, as signals generated therefrom and
9 phase coherent therewith, to transmit upstream data preceded by preamble data;
10 using said preamble data from each particular remote unit modem in said central
11 unit modem to determine the phase difference between said central unit modem master
12 clock and the clock signal used by that particular remote unit modem to transmit
13 upstream data and to determine the phase difference between said central unit modem
14 master carrier and the carrier of that particular remote unit modem to transmit
15 upstream data; and
16 using the phase differences so determined for each particular remote unit modem
17 to recover in said central unit modem the upstream payload data transmitted by that
18 particular remote unit modem.

1 5. A central unit modem apparatus comprising:
2 a framing circuit having a memory and circuitry to receive downstream data and
3 store it in said memory organized as frames of data each frame comprising one or more
4 symbols, and having circuitry to read data out of said memory and present said
5 downstream data at an output;

6 a transmitter coupled to receive said downstream data from said output and
7 having circuitry to multiplex said downstream data onto a transmission media using any
8 form of multiplexing and any form of modulation; and

9 a synchronous code division multiplexed receiver coupled to receive modulated
10 upstream signals from a plurality of remote unit modems and having circuitry to
11 demodulate and demultiplex said upstream signals and detect upstream data from said
12 demodulated, demultiplexed upstream signals.

1 6. The apparatus of claim 5 wherein said transmitter includes circuitry to transmit
2 downstream information defining the phase and frequency of a master clock signal and a
3 master carrier signal, and wherein said upstream signals include signals therein which
4 define the phase and frequency of clock and carrier signals used in said remote unit
5 modems to generate said upstream signals, and wherein said synchronous code division
6 multiplexed receiver includes tracking loop circuitry to track the phase and frequency of
7 the clock and carrier signals used by each remote unit modem and generate clock and
8 carrier signals locked in phase and frequency to the clock and carrier signals used in said
9 remote unit modem to generate said upstream signals, and circuitry to use said generated
10 clock and carrier signals to demodulate and demultiplex said upstream signals and detect
11 said upstream data from said demodulated, demultiplexed upstream signals.

1 7. The apparatus of claim 5 wherein said transmitter includes circuitry to transmit
2 downstream information defining the phase and frequency of a master clock signal and a
3 master carrier signal, and wherein said upstream signals include signals therein which
4 define the phase and frequency of the clock and carrier signals used by said remote unit
5 modems to generate said upstream signals wherein said clock and carrier signals used in
6 said remote unit modems to generate said upstream signals are locked in phase and
7 frequency with or are at least phase coherent with, master clock and master carrier
8 signals recovered from said downstream information transmitted by central unit
9 transmitter and wherein said upstream signals include preamble data transmitted by
10 each remote unit modem prior to transmission by that remote unit modem of any
11 upstream payload data, and wherein said synchronous code division multiplexed receiver
12 include circuitry to use said preamble data from each remote unit modem to determine
13 the phase differences for that particular remote unit modem between the master clock
14 and master carrier signals at said central unit modem and the clock and carrier signals

15 used by that particular remote unit modem as received at said central unit modem, and
16 for storing said phase differences in memory for use with said central unit modem
17 master clock and master carrier signals in demodulating, demultiplexing said upstream
18 signals and detecting upstream data therein, said circuitry for occasionally updating said
19 phase differences for each particular remote unit modem when said particular remote
20 unit modem again transmits preamble data.

1 8. A remote unit modem comprising:

2 a receiver circuit capable of demodulating and demultiplexing downstream signals
3 transmitted from a central unit modem regardless of the type of modulation and
4 multiplexing used by said central unit modem, and detecting and recovering downstream
5 payload data from said demodulated, demultiplexed downstream signals, and wherein said
6 downstream signals include information from which can be recovered a master clock and
7 master carrier signal used by said central unit modem in generating said downstream
8 signals, and wherein said receiver circuit further comprises circuitry to recover from
9 said downstream signals said master clock and master carrier signals and generate
10 remote unit clock and carrier signals therefrom which are locked in phase and frequency
11 with said recovered master clock and master carrier signals, and using said remote unit
12 clock and carrier signals so generated to demodulate and demultiplex said downstream
13 signals and to detect said downstream payload data from the demodulated, demultiplexed
14 downstream signals, said receiver including circuitry to detect a marker signal
15 transmitted from said central unit modem which marks a fixed reference time in each
16 frame of downstream data transmitted by said central unit modem and to generate a signal
17 indicating when said marker signal arrives, said receiver including circuitry to receive
18 management and control data from said central unit even before frame synchronization is
19 achieved;

20 a synchronous code division multiplexed transmitter coupled to receive said
21 remote unit clock and carrier signals, or clock and carrier signals which are at least
22 phase coherent with said remote unit clock and carrier signals, and coupled to receive
23 upstream payload data, said synchronous code division multiplexed transmitter including
24 ranging circuitry for achieving frame synchronization by transmitting ranging signals
25 with good correlation properties which can be found easily in noise and can be found even
26 if they arrive in the middle of payload data, said ranging circuitry for transmitting said
27 ranging signals at a series of different trial and error delays relative to said fixed

28 reference time in each frame of data transmitted by said central unit modem, the amount
29 of said delays established by a time delay input signal, said synchronous code division
30 multiplexed transmitter including multiplexing and modulation circuitry for code
31 division multiplexing said upstream payload data to generate spread spectrum data and
32 modulating the resulting spread spectrum data onto one or more RF carriers for
33 transmission to said central unit modem; and

34 a computer coupled to said receiver to receive said management and control data
35 and coupled to receive said signal indicating when said marker signal arrived from said
36 central unit modem, and including circuitry programmed to generate said time delay
37 input signal to control said trial and error delays used by said transmitter to transmit
38 said ranging signal and programmed to transmit said time delay input signal to said
39 synchronous code division multiplexed transmitter and programmed to vary the amount
40 of delay commanded by said time delay input signal relative to the time of receipt of said
41 marker signal and controlling the amount of power used to transmit said ranging signals
42 until said management and control data received from said central unit modem indicate
43 that a delay value T_d and a power level has been found which causes said ranging signals
44 to arrive within gaps in the central unit frames thereby achieving approximate frame
45 boundary alignment, and, thereafter, for holding the amount of delay T_d commanded by
46 said time delay input signal constant at the amount of delay which caused said
47 approximate frame boundary alignment.

1 9. The apparatus of claim 8 wherein said ranging circuitry and computer are structured
2 to perform boundless ranging in a system having a maximum total turnaround time of X
3 frames by performing the following steps:

4 (1) transmitting a Barker code upon every receipt of every marker signal
5 received from said central unit, each such Barker code transmission done a
6 predetermined delay T_d after receipt of said marker signal, said computer
7 programmed to start said transmissions at a first power level and a first delay
8 value and to increase said delay but leave the power level the same until all of a
9 predetermined number of delays have been tried, and then to repeat the process of
10 incrementing the delays at a new higher power level, and continue increasing the
11 power level and trying all of said predetermined delays until a message is
12 received from said central unit that a Barker code has been detected in a gap in
13 said central unit frames;

47 being equal to the time duration of one frame times said offset number plus the
48 value of T_d .

1 10. A remote unit modem comprising:

2 a receiver circuit capable of demodulating and demultiplexing downstream signals
3 transmitted from a central unit modem regardless of the type of modulation and
4 multiplexing used by said central unit modem, and detecting and recovering downstream
5 payload data from said demodulated, demultiplexed downstream signals, and wherein said
6 downstream signals include information from which can be recovered a master clock and
7 master carrier signal used by said central unit modem in generating said downstream
8 signals, and wherein said receiver circuit further comprises circuitry to recover from
9 said downstream signals said master clock and master carrier signals and generate
10 remote unit clock and carrier signals therefrom which are locked in phase and frequency
11 with said recovered master clock and master carrier signals, and using said remote unit
12 clock and carrier signals so generated to demodulate and demultiplex said downstream
13 signals and to detect said downstream payload data from the demodulated, demultiplexed
14 downstream signals, said receiver including frame detector circuitry to detect a Barker
15 code transmitted from said central unit modem during each gap between frames of
16 downstream data transmitted by said central unit, said Barker code marking the position
17 of each said gap in said stream of downstream data, said frame detector generating a
18 marker signal indicating when said barker code arrives, said receiver including
19 circuitry to receive management and control data from said central unit;

20 a synchronous code division multiplexed transmitter coupled to receive said
21 remote unit clock and carrier signals, or clock and carrier signals which are at least
22 phase coherent with said remote unit clock and carrier signals, and coupled to receive
23 upstream payload data, said synchronous code division multiplexed transmitter including
24 ranging circuitry for achieving exact frame synchronization by transmitting Barker
25 codes back to said central unit at a series of different trial and error delays T_d relative to
26 receipt of said marker signal, the amount of said delays T_d being controlled by a time
27 delay input signal, said synchronous code division multiplexed transmitter including
28 multiplexing and modulation circuitry for using said remote unit clock and carrier
29 signals or said clock and carrier signals which are at least phase coherent with said
30 remote unit clock and carrier signals to code division multiplex said upstream payload
31 data to generate spread spectrum data and to modulate the resulting spread spectrum data

32 onto one or more RF carriers for transmission as modulated RF signals to said central
33 unit modem, said synchronous code division multiplexed transmitter transmitting said
34 modulated RF signals in frames, each frame transmitted at an interval following
35 occurrence of said marker signal, said interval defined by the value of T_d which causes
36 each said frame to arrive with its frame boundaries exactly aligned in time with receive
37 frame boundaries of said central unit; and

38 a computer coupled to said receiver to receive said management and control data
39 and said marker signal, and including circuitry programmed to generate and increment
40 said time delay input signal to control said trial and error delays T_d used by said
41 transmitter to transmit said Barker code, said time delay input signal being coupled to
42 said synchronous code division multiplexed transmitter, said computer also programmed
43 to vary the amount of delay commanded by said time delay input signal relative to the
44 time of receipt of said marker signal until said management and control data received
45 from said central unit modem indicate that a delay value T_d has been found which causes
46 said Barker codes transmitted by said transmitter to arrive within gaps in central unit
47 frames, said computer programmed to further fine tune the value of said time delay
48 input signals until said Barker codes transmitted by said remote unit arrive exactly in
49 the middle of gaps in said central unit frames thereby achieving exact frame boundary
50 alignment with central unit frame boundaries.

1 11. The apparatus of claim 10 wherein said Barker code transmitted by said central
2 unit has encoded therein information defining the phase of a master clock signal used in
3 said central unit, and wherein said frame detector includes early-late gating circuitry
4 which generates a clock steering signal from which said remote unit master clock signal
5 can be generated using a phase lock loop in the remote unit.

1 12. The apparatus of claim 11 wherein said receiver includes a synthesizer which
2 generates said remote unit master carrier signal from either said remote unit master
3 clock signal or from said clock steering signal.

1 13. The apparatus of claim 10 wherein said receiver includes a synthesizer, a slicer, a
2 voltage controlled oscillator and a control loop including a loop filter for generating said
3 remote unit master carrier signal from BPSK modulated pilot channel data which
4 includes the phase information of the master carrier signal in said central unit, said

5 slicer generating a phase error signal by comparing the phase of the BPSK pilot channel
6 data actually received to what the phase should have been for pilot channel data modulated
7 using the master carrier and transmitted without latency and without channel
8 impairments, said phase error signal coupled to said voltage controlled oscillator
9 through said control loop to phase lock the phase of a carrier reference signal generated
10 by said voltage controlled oscillator to the phase of the master carrier at the central unit,
11 said carrier reference signal coupled to said synthesizer for controlling the phase of said
12 remote unit master carrier signal generated thereby.

1 14. The apparatus of claim 10 wherein each frame transmitted by said central unit has
2 a number and is followed by a gap, and wherein said remote unit modem is intended for
3 use in a distributed system having a plurality of other remote unit modems, and wherein
4 said synchronous code division multiplexed transmitter always uses the same orthogonal
5 spreading code or codes from the total set of orthogonal spreading codes used to spread the
6 spectrum of the upstream data, and wherein said ranging circuitry and said computer
7 combine to alter the value of said transmit frame timing delay T_d so as to exactly center
8 the Barker code transmitted by said synchronous code division multiplexed transmitter
9 in a gap in a central unit frame which may or may not be the same gap other remote unit
10 synchronous code division multiplexed transmitters have centered their Barker codes
11 within, wherein each gap is associated with a particular numbered frame at the central
12 unit.

1 15. A remote unit modem for use in a distributed system comprised of a plurality of
2 remote unit modems coupled by a shared transmission media to a central unit modem,
3 comprising:
4 a receiver circuit capable of demodulating and demultiplexing downstream signals
5 transmitted from a central unit modem regardless of the type of modulation and
6 multiplexing used by said central unit modem, and detecting and recovering downstream
7 payload data from said demodulated, demultiplexed downstream signals, and wherein said
8 downstream signals include information from which can be recovered a master clock and
9 master carrier signal used by said central unit modem in generating said downstream
10 signals, and wherein said receiver circuit further comprises circuitry to recover from
11 said downstream signals said master clock and master carrier signals and generate
12 remote unit clock and carrier signals therefrom which are locked in phase and frequency

13 with said recovered master clock and master carrier signals, and using said remote unit
14 clock and carrier signals so generated to demodulate and demultiplex said downstream
15 signals and to detect said downstream payload data from the demodulated, demultiplexed
16 downstream signals, said receiver including frame detector circuitry to detect a Barker
17 code transmitted from said central unit modem during each gap between frames of
18 downstream data transmitted by said central unit, said Barker code marking the position
19 of each said gap in said stream of downstream data, said frame detector generating a
20 marker signal indicating when said barker code arrives, said receiver including
21 circuitry to receive management and control data from said central unit;

22 a synchronous code division multiplexed transmitter coupled to receive said
23 remote unit clock and carrier signals, or clock and carrier signals which are at least
24 phase coherent with said remote unit clock and carrier signals, and coupled to receive
25 upstream payload data, said synchronous code division multiplexed transmitter including
26 boundless ranging circuitry for achieving exact frame synchronization by transmitting
27 Barker codes back to said central unit at a series of different trial and error delays T_d
28 relative to receipt of said marker signal, the amount of said delays T_d being controlled
29 by a time delay input signal, said synchronous code division multiplexed transmitter
30 including multiplexing and modulation circuitry for using said remote unit clock and
31 carrier signals or said clock and carrier signals which are at least phase coherent with
32 said remote unit clock and carrier signals to code division multiplex said upstream
33 payload data to generate spread spectrum data and to modulate the resulting spread
34 spectrum data onto one or more RF carriers for transmission as modulated RF signals to
35 said central unit modem, said synchronous code division multiplexed transmitter
36 transmitting said modulated RF signals in frames, each frame transmitted at an interval
37 following occurrence of said marker signal, said interval defined by the value of T_d
38 which causes each said frame to arrive with its frame boundaries approximately aligned
39 in time with receive frame boundaries of said central unit; and

40 a computer coupled to said receiver to receive said management and control data
41 and said marker signal, and including circuitry programmed to generate and increment
42 said time delay input signal to control said trial and error delays T_d used by said
43 transmitter to transmit said Barker code, said time delay input signal being coupled to
44 said synchronous code division multiplexed transmitter, said receiver and ranging
45 circuitry being structured in each remote unit and said computer so programmed in each

said remote unit so as to cooperate with said receiver and said ranging circuitry in said transmitter of each said remote unit modem to function in a way to carry out the following process to achieve approximate frame synchronization and rough power alignment:

(1) transmitting a Barker code a predetermined delay T_d following the occurrence of every marker signal, said computer programmed to start said Barker code transmissions at a first power level and at a first minimum value for delay T_d and to increase said delay every frame and re-transmit another Barker code while leaving the power level the same until a maximum value for delay T_d is reached, and then to repeat the process of incrementing the value of the delay T_d at a new higher power level than the power level used during the previous cycle, and continue increasing the power level and trying all of said predetermined delays at that power level until a first command and control message is received from said central unit indicating that a possible Barker code has been detected in a gap in said central unit frames;

(2) once said first message has been received from said central unit that a possible Barker code has been detected in a gap, said computer assumes the activity detected was one of the prior Barker code transmissions from this remote unit, and determines which delay value T_d of the multiple values for T_d previously used to send Barker codes caused a Barker code from this remote unit to arrive during a central unit gap by setting the delay T_d to the value used X frames before said first message was received where X is equal to the total turnaround time in whole frames to the farthest remote unit in the distributed system, sending a single Barker code transmission using that delay value, and waiting at least X frames for a second reply message from said central unit indicating that a Barker code was received during a central unit receive frame gap;

(3) if no second reply message is received during said X frames, incrementing the value for delay T_d in said computer to the value used to transmit the Barker code in the $X + 1$ frame which is defined as the frame which followed the frame corresponding to the value for T_d selected in step 2 and sending said incremented delay value to said ranging circuitry to cause it to transmit another

78 Barker code at a time following receipt of the next marker signal by an interval
79 equal to said incremented delay value, and waiting the duration of X frames for
80 said second reply message, and continuing this process of incrementing the value
81 of T_d to each of the values used at each of the X preceding frames, transmitting a
82 single Barker code and waiting X frames for receipt of said second reply message
83 until said second reply message is received from the central unit indicating
84 activity has been detected in a gap and naming a first central unit frame number
85 having a gap in which a Barker code was detected and requesting the remote unit
86 to send the ID code for that remote unit, and holding the value of delay T_d steady at
87 the value which resulted in transmission of said second reply message;

88 (4) using said ranging circuitry at the request of said computer to
89 transmit an ID code comprising a start bit which is always a 1 and a
90 predetermined number of ID bits a predetermined number of which are 1s and
91 the rest of which are 0s, with a 1 being defined as the transmission of a Barker
92 code in a gap and a 0 defined as the lack of transmission of a Barker code in a gap;

93 (5) receiving a third reply message from said central unit when said
94 central unit receives said start bit and said ID code and detects therein a
95 predetermined number of 1s indicative of the fact that no other remote unit's ID
96 code arrived at the same time at the central unit thereby indicating no contention,
97 said third reply message containing at least the ID code detected by the central
98 unit and the central unit frame number during which said start bit of said ID code
99 arrived, said ranging circuitry and said computer structured and programmed to
100 compare the ID code in said third reply message against the ID code transmitted
101 by said remote unit modem, and, if there is a match, to calculate a frame offset
102 number needed to achieve boundless ranging, said frame offset number being
103 comprised of the frame number given in said third reply message minus the
104 frame number given in said second reply message; and

105 (6) thereafter receiving command and control messages assigning particular
106 orthogonal spreading codes to be used during particular central unit receive
107 frame numbers and counting marker signals to generate a count indicating the
108 central unit frame number just received and subtracting said offset number
109 therefrom to generate a new frame count and controlling said synchronous code
110 division multiplexed transmitter in said remote unit to transmit each numbered
111 frame to the central unit delayed by the current value for the delay T_d when said

112 new frame count reaches a frame number authorized for transmission by said
113 central unit and using the orthogonal spreading codes assigned by said central unit
114 to code division multiplex the data to be transmitted during said assigned frame
115 number.

1 16. The apparatus of claim 15 wherein said receiver, ranging circuitry and computer of
2 each said remote unit modem are structured to carry out the following further functions
3 to implement a fine tuning process to achieve exact centering of the Barker code from
4 each remote unit modem in the center of the gap following the same central unit frame
5 number:

6 (1) waiting for a fourth reply message from said central unit indicating
7 fine tuning is to be performed by that particular remote unit modem and
8 adjusting the value of delay T_d and transmitting a Barker code and waiting for a
9 fine tuning feedback message from said central unit and continuing to adjust the
10 value of the delay T_d until a message is received indicating that said Barker code
11 has arrived in the center of a listening window in a gap of a central unit frame.

1 17. The apparatus of claim 16 wherein said receiver, ranging circuitry and computer of
2 each said remote unit modem are structured to carry out the following further functions
3 to implement a contention resolution process such that multiple remote unit modems can
4 all perform ranging simultaneously:

5 (1) receiving a message from said central unit containing the previous
6 ID code sent by the remote unit modem and requesting transmission of another ID
7 code, and responding thereto by transmitting another randomly selected ID code
8 having a start bit which is a 1 and a predetermined number of 1s in an ID code
9 having a predetermined number of bits in a like number of consecutive frames;

10 (2) waiting for a message from said central unit containing the new ID
11 code just sent, and, if said message is received, stopping the ranging process, but
12 if a message is received from said central unit indicating that a contention has
13 been detected, performing a contention resolution process of deciding whether to
14 continue ranging with a predetermined probability of continuing to perform the
15 ranging process.

1 18. A process for fine tuning the amount of power with which data is transmitted to a
2 central unit receiver by each of a plurality of remote unit transmitters which are
3 physically spread throughout a distributed digital data communication system, using code
4 division multiple access multiplexing accomplished with orthogonal, cyclic spreading
5 codes for transmissions, each said remote unit transmitter having a variable gain
6 amplifier, and wherein said central unit has a receiver having an adaptive gain control
7 circuit comprised of a slicer and an amplifier having a variable gain the gain control
8 factor of which is controlled by an amplitude correction factor stored in memory, said
9 memory storing an amplitude correction factor for each said spreading code and a control
10 circuit that receives slicer amplitude error signals from said slicer and controls the
11 gain number applied to said amplifier, comprising the following steps performed one at a
12 time in each remote unit transmitter:

13 (1) transmitting training data from a remote unit transmitter to
14 said central unit receiver using a gain level of one in said remote unit
15 transmitter variable gain amplifier, the spectrum of said training data having
16 been spread using each of a plurality of consecutive, orthogonal, cyclic spreading
17 codes, and modulating the training data using BPSK modulation;

18 (2) setting the gain of said variable gain amplifier using the amplitude
19 correction factor for a particular one of the codes in the midst of said
20 consecutive, orthogonal, cyclic spreading codes, and allowing said adaptive gain
21 control circuit to converge on an amplitude correction factor for the training data
22 that results in proper decisions on said training data made by said slicer and
23 adjusting the gain of said variable gain amplifier to a new gain value in
24 accordance with said amplitude correction factor so determined;

25 (3) transmitting said new gain value to said remote unit transmitter and
26 setting the power level of transmissions by said remote unit transmitter in
27 accordance with said new gain value; and

28 (4) setting the gain control factor of said variable gain amplifier in said
29 central unit to one.

1 19. A process for fine tuning the amount of power with which data is transmitted to a
2 central unit receiver by each of a plurality of remote unit transmitters which are
3 physically spread throughout a distributed digital data communication system, using code
4 division multiple access multiplexing accomplished with orthogonal, cyclic spreading

5 codes for transmissions, and wherein said central unit has a receiver having an symbol
6 equalizer having at least an FFE digital adaptive filter having a main tap and one or more
7 side taps, comprising the following steps performed one at a time in each remote unit
8 transmitter:

9 (1) setting an adaptation coefficient in said symbol equalizer to a value
10 selected to insure rapid convergence;

11 (2) transmitting training data from a remote unit transmitter to said
12 central unit receiver the spectrum of said training data having been spread using
13 each of a plurality of consecutive, orthogonal, cyclic spreading codes, and
14 modulating the training data using BPSK modulation;

15 (3) disabling said one or more side taps and enabling said symbol
16 equalizer filter to converge for an interval sufficient to train said main tap
17 adequately for purposes of power alignment;

18 (4) calculating the amplitude of the main tap correction factor after said
19 interval has elapsed and comparing said amplitude the expected amplitude of said
20 main tap when proper power alignment has been achieved and calculating the
21 difference and comparing said difference or said difference divided by a constant
22 to a threshold;

23 (5) if said threshold is exceeded, transmitting a new gain value to said
24 remote unit transmitter, said new gain value being equal to said difference times
25 a constant and setting the power level of transmissions by said remote unit
26 transmitter in accordance with said new gain value; and

27 (4) repeating steps 1 through 5 until said difference is less than said
28 threshold or a predetermined number of iterations of steps 1 through 5 has been
29 exceeded.

1 20. A digital data communication apparatus including frame synchronization fine tuning
2 circuitry, comprising:

3 a central unit transceiver having a transmitter which transmits
4 downstream data in CU downstream frames separated by gaps using master clock
5 and master carrier signals which are both synthesized from a single crystal
6 oscillator source and which transmits a marker signal during every CU
7 downstream frame gap, said marker signal bearing at least phase information
8 defining the phase of said master clock, said central unit transceiver also having

a receiver which receives upstream data in CU upstream frames separated by gaps;

a remote unit transceiver having a transmitter which transmits said upstream data in RU upstream frames separated by gaps, said RU upstream frames and gaps having the same duration as said CU upstream frames and gaps to said central unit receiver and including ranging circuitry which transmits a ranging signal to achieve frame synchronization so as to exactly align said RU upstream frame boundaries with said CU upstream frame boundaries, said remote unit transceiver having a receiver circuitry to receive said marker signal and command and control messages transmitted in said CU downstream frames, said ranging signal transmitted during the process of achieving frame synchronization during selected RU upstream frames at a delay T_d following receipt of said marker signal, said remote unit receiver including synchronization circuitry to recover said master clock and master carrier signals from said marker signal, a correlator to correlate said received downstream signals against a signal having the shape and duration of said marker signal so as to locate said marker signal so as to generate a correlation peak when said marker signal is found and said CU downstream frame gap is located thereby, and having early-late gating circuitry to sample said correlation peak at two different points on either side of the maximum amplitude of said correlation peak to generate a clock steering signal during each CU downstream frame and having clock tracking loop circuitry to generate a local master clock signal from said clock steering signal, and having synthesizer circuitry to generate a local master carrier signal from phase information in said local master clock signal, said remote unit transmitter using said local master clock and local master carrier signals or signals that are phase coherent therewith to transmit said RU upstream frames, and including circuitry to transmit, at predetermined times, preamble data before transmitting said RU upstream frames, said preamble data being such that said central unit receiver can determine phase and amplitude error correction factors therefrom so that said central unit receiver can recover said local master clock and local master carrier signals used by said remote unit transmitter and to properly demodulate and detect data in said RU upstream frames, said correction factors being made necessary by latency and channel impairments, said remote unit transmitter including circuitry to alter said delay T_d by trial and error for different

43 transmissions of said ranging signal, and wherein said remote unit receiver
44 includes circuitry to receive command and control messages from said central
45 unit transmitter regarding changing the value of said delay T_d , and changing the
46 value of delay T_d in accordance therewith;

47 and wherein said central unit receiver includes ranging circuitry,
48 including correlation circuitry structured so as to find said ranging signals, and
49 including circuitry to compare the position of said ranging signals to the centers
50 of said CU upstream frame gaps and generate messages for transmission to said
51 remote unit to cause said delay T_d to be altered until said ranging signals arrive
52 exactly in the center of CU upstream frame gaps so as to exactly align said RU
53 upstream frame boundaries with said CU upstream frame boundaries, and further
54 including circuitry to receive said preamble data from each remote unit and
55 derive therefrom amplitude and phase error correction factors to aid in the
56 process of recovering digital data transmitted in said RU upstream frames.

1 21. The apparatus of claim 20 wherein said CU receiver correlation circuitry includes
2 circuitry to correlate received upstream signals against a signal having the same shape
3 and duration as said ranging signal to generate a correlation peak and to perform a course
4 time alignment to get said ranging signal within a predetermined distance from the center
5 of said CU upstream frame gaps and further comprises circuitry to perform fine tuning
6 centering by performing early-late gating sampling on said correlation peak and
7 determine the difference between said early and late samples and average a plurality of
8 said differences to average out any random noise content, and to use the sign of the
9 averaged differences to generate steering commands to send to said remote unit to cause
10 alteration of said delay T_d , said ranging circuitry repeating the steps described herein
11 until said ranging signals are aligned exactly in the center of said CU upstream frame
12 gap.

1 22. The apparatus of claim 21 wherein a plurality of said remote unit transceivers are
2 physically spread throughout a distributed communication system, and wherein said
3 central unit downstream and upstream frame boundaries are coincident in time and have
4 the same frame numbers, and wherein said ranging signal is a Barker code, and wherein

each of said plurality of remote unit transceivers and said central unit transceiver include circuitry to perform boundless ranging by performing the following functions:

(1) transmitting from said remote unit transmitter a Barker code a predetermined delay T_d following the receipt by said remote unit receiver of every marker signal during the ranging process to achieve frame synchronization, said ranging circuitry of said remote unit transmitter structured to start said Barker code transmissions at a first power level and at a first minimum value for delay T_d and to increase said delay every RU upstream frame and re-transmit another Barker code while leaving the power level the same until a maximum value for delay T_d is reached, and then to repeat the process of incrementing the value of the delay T_d at a new higher power level than the power level used during the previous cycle of delay incrementations, and continue increasing the power level and trying all of said predetermined delays T_d at that power level until a first command and control message is received from said central unit transceiver indicating that a possible Barker code has been detected in a gap in said central unit frames;

(2) once said first message has been received from said central unit that a possible Barker code has been detected in a gap, said remote unit transmitter ranging circuitry being structured to assume that the activity detected was one of the prior Barker code transmissions from this remote unit transceiver, said remote unit transmitter ranging circuitry structured to then determine which delay value T_d of the multiple values for T_d previously used to send Barker codes caused a Barker code from this remote unit to arrive during a central unit gap, said determination being made by setting the delay T_d to the value used X frames before said first message was received where X is equal to the total turnaround time in whole frames to the farthest remote unit transceiver in said distributed system, sending a single Barker code transmission using that delay value, and waiting at least X frames for a second reply message from said central unit transceiver indicating that a Barker code was received during a central unit upstream frame gap;

(3) if no second reply message is received during said X frames, said remote unit transmitter ranging circuitry is structured to increment the value

38 for delay T_d to the value used to transmit the Barker code in the $X + 1$ frame,
39 where the $X + 1$ frame is defined as the frame which followed the frame
40 corresponding to the value for T_d selected in step 2, said remote unit ranging
41 circuitry being structured to use said incremented delay value to transmit the
42 next said ranging signal and wait an interval of X frames for said second reply
43 message, said remote unit ranging circuitry structured to continue this process
44 of incrementing the value of T_d to each of the values used at each of the X
45 preceding frames, transmitting a single Barker code and waiting X frames for
46 receipt of said second reply message until said second reply message is received
47 by said remote unit receiver from the central unit transceiver indicating activity
48 has been detected in a central unit frame gap and indicating the central unit frame
49 number having the gap in which a Barker code was detected, said second reply
50 message resulting in a signal being passed to said remote unit ranging circuitry
51 requesting same to transmit an ID code for that remote unit, and holding the value
52 of delay T_d steady at the value which resulted in a Barker code transmission
53 arriving in a gap in a central unit upstream frame;

54 (4) said remote unit ranging circuitry structured to respond to said
55 second reply message by transmitting an ID code comprising a start bit which is
56 always a 1 and a predetermined number of ID bits a predetermined number of
57 which are 1s and the rest of which are 0s, with a 1 being defined as the
58 transmission of a Barker code in a gap and a 0 defined as the lack of transmission
59 of a Barker code in a gap;

60 (5) receiving a third reply message in said remote unit receiver
61 generated by said central unit transceiver when said central unit transceiver
62 receives said start bit and said ID code and detects therein a predetermined
63 number of 1s indicative of the fact that no other remote unit's ID code arrived at
64 the same time at the central unit thereby indicating no contention between
65 different remote unit transceivers, said third reply message containing at least
66 the ID code detected by the central unit transceiver and the central unit frame
67 number during which said start bit of said ID code arrived, said ranging circuitry
68 structured to compare the ID code in said third reply message against the ID code
69 transmitted by said remote unit transceiver, and, if there is a match, to calculate
70 a frame offset number needed to achieve boundless ranging, said frame offset

7 1 number being comprised of the frame number given in said third reply message
 7 2 minus the frame number given in said second reply message; and
 7 3 (6) said central unit transceiver structured to generate and transmit to
 7 4 each said remote unit transceiver command and control channel assignment
 7 5 messages assigning particular orthogonal spreading codes, timeslots, frequencies
 7 6 or other channel multiplexing attributes to be used by said remote unit
 7 7 transceiver during particular central unit frame numbers, said remote unit
 7 8 transceiver including circuitry structured to count marker signals received
 7 9 from said central unit transceiver to generate a count indicating the current
 8 0 central unit frame number and subtract said offset number therefrom to generate
 8 1 an upstream transmit frame count, said remote unit transmitter including
 8 2 circuitry to receive said channel assignment message information from said
 8 3 remote unit receiver and to use said upstream transmit frame count and the
 8 4 current value for delay T_d to transmit each numbered frame of upstream data to
 8 5 the central unit transceiver using the assigned channel when said upstream
 8 6 transmit frame count reaches a frame number authorized for transmission by
 8 7 this remote unit transceiver by said central unit transceiver.

1 23. The apparatus of claim 22 wherein said central unit transceiver and said remote
 2 unit transceiver each further comprise means for performing equalization training so as
 3 to predistort transmissions to minimize the effect on the detection process of phase and
 4 amplitude errors induced by channel impairments.

1 24. The apparatus of claim 20 wherein said remote unit transmitter includes a precode
 2 equalization filter in the form of a digital FFE filter having multiple coefficients, and
 3 wherein said remote unit transceiver includes circuitry for receiving command and
 4 control communications from said central unit transceiver instructing changes in the
 5 value of said delay T_d and for multiplying the coefficients of said FFE filter in said
 6 remote unit transmitter by the negative of the phase shift at said central unit
 7 transceiver of signals received from this remote unit transceiver which will be caused
 8 by the change in the delay T_d at said remote unit transceiver for subsequent
 9 transmissions so as to provide phase shift compensation.

1 25. The apparatus of claim 21 wherein said remote unit transmitter includes a precode
2 equalization filter in the form of a digital FFE filter having multiple coefficients, and
3 wherein said remote unit transceiver includes circuitry for receiving comand and
4 control communications from said central unit transceiver instructing changes in the
5 value of said delay T_d and for multiplying the coefficients of said FFE filter in said
6 remote unit transmitter by the negative of the phase shift at said central unit
7 transceiver of signals received from this remote unit transceiver which will be caused
8 by the change in the delay T_d at said remote unit transceiver for subsequent
9 transmissions so as to provide phase shift compensation.

1 26. The apparatus of claim 22 wherein said remote unit transmitter includes a precode
2 equalization filter in the form of a digital FFE filter having multiple coefficients, and
3 wherein said remote unit transceiver includes circuitry for receiving comand and
4 control communications from said central unit transceiver instructing changes in the
5 value of said delay T_d and for multiplying the coefficients of said FFE filter in said
6 remote unit transmitter by the negative of the phase shift at said central unit
7 transceiver of signals received from this remote unit transceiver which will be caused
8 by the change in the delay T_d at said remote unit transceiver for subsequent
9 transmissions so as to provide phase shift compensation.

1 27. The apparatus of claim 23 wherein said remote unit transmitter includes a precode
2 equalization filter in the form of a digital FFE filter having multiple coefficients, and
3 wherein said remote unit transceiver includes circuitry for receiving comand and
4 control communications from said central unit transceiver instructing changes in the
5 value of said delay T_d and for multiplying the coefficients of said FFE filter in said
6 remote unit transmitter by the negative of the phase shift at said central unit
7 transceiver of signals received from this remote unit transceiver which will be caused
8 by the change in the delay T_d at said remote unit transceiver for subsequent
9 transmissions so as to provide phase shift compensation.

1 28. A bidirectional digital data communication system including a central unit
2 transceiver having circuitry for accepting downstream data from multiple sources
3 organized into a time division multiplexed stream of data and assembling symbol data

therefrom, and including multiplexer and modulator circuits for code division multiplexing said downstream symbol data and modulating the resulting multiplexed data onto one or more RF carriers and transmitting the resulting downstream RF signals on a shared media and including a plurality of remote unit transceivers including demodulating and demultiplexing circuitry to demodulate said downstream signals and demultiplex the resulting demodulated signals and including deframer circuitry for receiving the resulting demultiplexed data and reassembling a time division multiplexed stream of data therefrom, said remote unit transceivers including circuitry to receive upstream data from multiple sources in time division multiplexed streams and assemble upstream symbols therefrom, and including multiplexing and modulator circuitry to code division multiplex said upstream symbol data and modulate the resulting multiplexed data onto one or more RF carriers and transmit the resulting upstream RF signals on said shared media using frequency division multiple access to separate the upstream RF signals from the downstream RF signals, said central unit transceiver including demodulator and demultiplexing circuitry to demodulate and demultiplex the upstream RF signals and including deframer circuitry to receive the demultiplexed upstream data and reassemble a time division multiplexed data stream therefrom.

29. A distributed communication system having a central unit transceiver coupled by a shared transmission media to a plurality of remote unit transceivers wherein said remote unit transceivers and said central unit transceiver include circuitry to bidirectionally communicate digital data using any form of multiplexing and any form of modulation using a single master clock and a single master carrier, both said master clock and said master carrier being synthesized in said central unit transceiver from a single crystal controlled oscillator, said master clock and master carrier signals being transmitted downstream to said remote units and recovered there and used by each remote unit transceiver to transmit data upstream to said central unit, each said remote unit transmitting its upstream data after transmitting at least some preamble data, said central unit transceiver including circuitry to use said preamble data from each remote unit transceiver to determine amplitude and phase correction factors for use in receiving data from said remote unit transceiver by correcting for phase and amplitude errors caused by channel impairments and the transmission delay between said remote unit transceiver and said central unit transceiver.

1 30. A distributed communication system having a central unit transceiver coupled by a
2 shared transmission media to a plurality of remote unit transceivers wherein said
3 remote unit transceivers and said central unit transceiver include circuitry to
4 bidirectionally communicate digital data in synchronized frames separated by gaps using
5 any form of multiplexing and any form of modulation wherein each said remote unit
6 transceiver and said central unit transceiver include ranging circuitry to carry out a
7 ranging process before upstream data is transmitted whereby each said remote unit
8 transceiver receives a marker signal from said central unit transceiver and transmits
9 ranging signals at different values of a delay T_d following receipt of said marker signal
10 until a delay T_d is found which causes the ranging signals to arrive at said central unit
11 transceiver exactly in the middle of a gap between central unit transceiver frames such
12 that frame boundaries of frames transmitted by each said remote unit transceiver arrive
13 exactly aligned in time with frame boundaries of said central unit frames.

1 31. A distributed communication system having a central unit transceiver coupled by a
2 shared transmission media to a plurality of remote unit transceivers wherein said
3 remote unit transceivers and said central unit transceiver include circuitry to
4 bidirectionally communicate digital data in synchronized frames separated by gaps using
5 any form of multiplexing and any form of modulation wherein each said remote unit
6 transceiver and said central unit transceiver include ranging circuitry to carry out a
7 ranging process before upstream data is transmitted whereby each said remote unit
8 transceiver receives a marker signal from said central unit transceiver and transmits
9 ranging signals at different values of a delay T_d following receipt of said marker signal
10 until a delay T_d is found which causes the ranging signals to arrive at said central unit
11 transceiver exactly in the middle of a gap between central unit transceiver frames such
12 that frame boundaries of frames transmitted by each said remote unit transceiver arrive
13 exactly aligned in time with frame boundaries of said central unit frames, and wherein
14 said central unit transceiver transmits said said marker signals and data in downstream
15 frames using a single master clock and a single master carrier, both said master clock
16 and said master carrier being synthesized in said central unit transceiver from a single
17 crystal controlled oscillator, said master clock and master carrier signals being
18 transmitted downstream to said remote units in any known fashion and recovered there
19 and used by each remote unit transceiver to transmit data upstream to said central unit

20 in frames, each said remote unit transceiver transmitting its upstream data after
21 transmitting at least some preamble data, said central unit transceiver including
22 circuitry to use said preamble data from each remote unit transceiver to determine
23 amplitude and phase correction factors for use in conjunction with said master clock and
24 master carrier signals generated in said central unit transceiver to receive data from
25 said remote unit transceiver by correcting for phase and amplitude errors caused by
26 channel impairments and the transmission delay between said remote unit transceiver
27 and said central unit transceiver thereby eliminating the need for continuous tracking
28 loops in said central unit transceiver to recover the clock and carrier signals used by
29 said remote unit to transmit upstream data.

1 32. The apparatus of claim 30 wherein at least said remote unit transceivers use code
2 division multiplexing as the form of multiplexing to keep data from different sources
3 separate.

1 33. The apparatus of claim 30 wherein at least said remote unit transceivers use time
2 division multiple access as the form of multiplexing to keep data from different sources
3 separate.

1 34. The apparatus of claim 30 wherein at least said remote unit transceivers use
2 inverse Fourier as the form of multiplexing to keep data from different sources separate.

1 35. The apparatus of claim 30 wherein at least said remote unit transceivers use digital
2 multitone as the form of multiplexing to keep data from different sources separate.

1 36. The apparatus of claim 30 wherein at least said remote unit transceivers use
2 frequency division multiple access as the form of multiplexing to keep data from
3 different sources separate.

1 37. The apparatus of claim 31 wherein at least said remote unit transceivers use code
2 division multiplexing as the form of multiplexing to keep data from different sources
3 separate.

1 38. The apparatus of claim 31 wherein at least said remote unit transceivers use time
2 division multiple access as the form of multiplexing to keep data from different sources
3 separate.

1 39. The apparatus of claim 31 wherein at least said remote unit transceivers use
2 inverse Fourier as the form of multiplexing to keep data from different sources separate.

1 40. The apparatus of claim 31 wherein at least said remote unit transceivers use digital
2 multitone as the form of multiplexing to keep data from different sources separate.

1 41. The apparatus of claim 31 wherein at least said remote unit transceivers use
2 frequency division multiple access as the form of multiplexing to keep data from
3 different sources separate.

1 42. A digital data communication system having a plurality of transceivers
2 bidirectionally communicating digital data wherein said transceivers transmitting data
3 in at least one direction use code division multiple access multiplexing to keep different
4 conversations separate, where conversation is defined as transmission of data from one
5 source or computer process to another different source or computer process via at least
6 two transceivers, and wherein said transceivers include means for transmitting data in
7 frames and in a frame synchronous manner such that frames of data from physically
8 distributed transceivers all arrive at a predetermined location with their frame
9 boundaries aligned in time.

1 43. The apparatus of claim 42 further comprising means coupled to each transceiver
2 which uses code division multiple access multiplexing, for pseudorandomly changing the
3 spreading codes used during designated frames for transmission of each conversation.

1 44. The apparatus of claim 42 wherein said transceivers include means for receiving
2 incoming data in timeslots of a TDMA stream, breaking the data from each timeslot into
3 smaller groups of bits, Trellis encoding each group of bits to add a predetermined
4 number of redundant bits in a normal mode and a larger number of redundant bits in a
5 fallback mode when channel impairments require more redundant bits, and interleaving
6 the Trellis encoded groups of bits over one or more frames, generating a plurality of

7 symbols from said interleaved groups of bits, spreading the spectrum of said symbols
8 and modulating the resulting digital data into the radio frequency spectrum using
9 carrierless modulation and orthogonal bandpass filters to limit the bandwidth of each of
10 real and imaginary components to a predetermined bandwidth, said bandpass filters
11 having transfer functions one of which is the Hilbert transform of the other.

1 45. The apparatus of claim 44 wherein each transceiver includes means for
2 demodulating, demultiplexing and detecting the signals output from the demultiplexing
3 process with a slicer, rotational amplifier and symbol equalizer to generate preliminary
4 decision data and then Viterbi decoding the output data from said slicer in a Viterbi
5 decoder, and using the output data from said Viterbi decoding process to reassemble the
6 original TDMA stream.

1 46. The apparatus of claim 42 wherein said transceivers using code division multiple
2 access multiplexing use orthogonal spreading codes, and wherein one of said transceivers
3 is a central unit transceiver having a bandwidth allocation means therein for receiving
4 requests for bandwidth from said remote unit transceivers, making decisions regarding
5 how to allocate limited bandwidth to said remote unit transceivers based upon any of a
6 plurality of different sets of dynamic bandwidth allocation rules including but not
7 limited to reservation, first-come, first-served, first-come, first-served with
8 bandwidth guarantees to selected transceivers and for transmitting bandwidth allocation
9 decisions to transceivers in downstream messages, and wherein the other transceivers
10 are remote unit transceivers each having means therein to cooperate to implement the
11 bandwidth allocation scheme in use by receiving bandwidth allocation messages assigning
12 specific codes to use during specific frames, and using said codes to spread the spectrum
13 of data to be transmitted to said central unit transceiver during the specified frames.

1 47. A digital data communication system having a plurality of transceivers
2 bidirectionally communicating digital data between a central unit transceiver and a
3 plurality of distributed remote unit transceivers, and wherein at least said remote unit
4 transceivers transmit data to said central unit transceiver using code division multiple
5 access multiplexing to keep conversations between different remote unit transceivers
6 and said central unit transceiver separate, where conversation is defined as
7 transmission of data from one source or computer process to another different source or

8 computer process via at least two transceivers, and wherein said central unit
9 transceiver transmits data downstream to said remote unit transceivers in frames
10 separated by gaps, and wherein said remote unit transceivers include ranging means for
11 transmitting data in upstream frames in a frame synchronous manner such that
12 upstream frames of data from physically distributed transceivers all arrive at said
13 central unit transceiver with their frame boundaries exactly aligned in time, and
14 wherein each remote unit transceiver uses permanently assigned orthogonal spreading
15 codes.

1 48. The apparatus of claim 47 further comprising equalization means in said
2 transceivers for cooperating to determine separate equalization coefficients for digital
3 filters in each said remote unit transceiver to correct for channel impairments that
4 signals from that remote unit transceiver will suffer in propagating to said central unit
5 transceiver.

1 49. A digital data communication system having a plurality of transceivers
2 bidirectionally communicating digital data between a central unit transceiver and a
3 plurality of distributed remote unit transceivers, and wherein at least said remote unit
4 transceivers transmit data to said central unit transceiver using code division multiple
5 access multiplexing to keep conversations between different remote unit transceivers
6 and said central unit transceiver separate, where conversation is defined as
7 transmission of data from one source or computer process to another different source or
8 computer process via at least two transceivers, and wherein said central unit
9 transceiver transmits data downstream to said remote unit transceivers in numbered
10 frames separated by gaps, and wherein each remote unit transceiver uses temporarily
11 assigned cyclic, orthogonal time shared spreading codes during specific frame numbers
12 for transmission to said central unit transceiver after receiving assignments of specific
13 codes to use during specific frames from said central unit transceiver, and wherein each
14 said remote unit transceiver includes boundless ranging means for transmitting data in
15 upstream frames in a frame synchronous manner such that all upstream frames of data
16 transmitted from physically distributed transceivers at different delays after receipt of
17 any particular frame number from the central unit transceiver and having the spectra
18 thereof spread with codes assigned to said remote unit transceivers for use during a
19 specific central unit transceiver frame number arrive at said central unit transceiver

20 with their frame boundaries exactly aligned in time with the boundaries of the central
21 unit frame having said specific frame number.

1 50. The apparatus of claim 49 further comprising equalization means in said central
2 unit and remote unit transceivers for cooperating to determine separate equalization
3 coefficients for digital filters in each said remote unit transceiver and said central unit
4 transceiver to correct for amplitude and phase errors caused by channel impairments
5 that affect signals propagating from that remote unit transceiver to said central unit
6 transceiver.

1 51. The apparatus of claim 50 further comprising power alignment means in said
2 remote unit transceivers and said central unit transceiver for cooperating to fine tune
3 the power level of transmissions from said remote unit transceivers to said central unit
4 transceiver such that all transmissions arrive at approximately the same power level.

1 52. The apparatus of claim 51 further comprising equalization means in said central
2 unit and remote unit transceivers for cooperating to determine separate equalization
3 coefficients for digital filters in said remote unit transceiver and said central unit
4 transceiver to correct for amplitude and phase errors caused by channel impairments
5 that affect signals propagating from that central unit transceiver to each said remote
6 unit transceiver.

1 53. A digital data communication system having a plurality of transceivers
2 bidirectionally communicating digital data between a central unit transceiver and a
3 plurality of distributed remote unit transceivers, and wherein at least said remote unit
4 transceivers transmit data to said central unit transceiver using code division multiple
5 access multiplexing to keep conversations between different remote unit transceivers
6 and said central unit transceiver separate, where, conversation is defined as
7 transmission of data from one source or computer process to another different source or
8 computer process via at least two transceivers, and wherein said central unit
9 transceiver transmits data downstream to said remote unit transceivers in frames
10 separated by gaps, and wherein said remote unit transceivers include ranging means for
11 transmitting data in upstream frames in a frame synchronous manner such that
12 upstream frames of data from physically distributed transceivers all arrive at said

1 3 central unit transceiver with their frame boundaries exactly aligned in time to a same
1 4 central unit frame, all remote unit transceivers having their frame boundaries aligned
1 5 in time with the frame boundaries of the same central unit frame, and wherein each
1 6 remote unit transceiver uses temporarily assigned orthogonal spreading codes.

1 54. The apparatus of claim 53 wherein a predetermined number of spreading codes are
2 reserved as access channels for upstream requests from remote unit transceivers to the
3 central unit transceiver for bandwidth allocation, and further comprising media access
4 control means in said central unit transceiver and said remote unit transceivers for
5 sharing said access channels with all remote unit transceivers to send bandwidth
6 allocation messages to said central unit transceiver, resolve contentions between
7 different remote unit transceivers for use of the same access channel, receive bandwidth
8 allocation messages and use the assigned codes for transmissions to said central unit
9 transceiver.

1 55. A process for media access control in a CDMA digital data communication system
2 having a first plurality of access channels and a second, much larger plurality of payload
3 data channels and having a plurality of remote unit transceivers which transmit data to a
4 central unit transceiver using spreading codes assigned by said central unit transceiver,
5 comprising:

6 sending a seed number to all said remote unit transceivers;

7 each remote unit transceiver needing to send a bandwidth request message
8 then uses said seed number to pseudorandomly select one of said access channels
9 to use to send said bandwidth request message;

1 0 each remote unit transceiver needing to send a bandwidth request message
1 1 then uses said seed number to pseudorandomly select a first plurality of symbols
1 2 of a superframe comprised of a second, larger plurality of symbols to send as a
1 3 bandwidth request message;

1 4 listening on all access channels in said central unit transceiver to
1 5 determine if more than said first plurality of symbols was received, indicating a
1 6 contention between two or more remote unit transceivers for the same access
1 7 channel;

18 if a contention is detected, sending a contention detected message
19 downstream indicating a contention of a particular access channel to all remote
20 unit transceivers;
21 in each remote unit transceiver attempting to send a bandwidth request
22 message on that access channel, receiving said contention detected message and
23 making a decision as to whether to continue requesting access with a 50%
24 probability of continuing to request access;
25 if no contention is detected, broadcasting a message to all remote unit
26 transceivers identifying which first plurality of symbols was received indicating
27 to the remote unit transceiver which transmitted said first plurality of symbols
28 that it now has sole control of said access channel for bandwidth request message
29 traffic.

1 56. A process for bandwidth allocation in a CDMA digital data communication system
2 having a plurality of payload data channels and having a plurality of remote unit
3 transceivers which transmit data to a central unit transceiver using spreading codes
4 assigned by said central unit transceiver, each spreading code representing one payload
5 data channel and wherein the number of said remote unit transceivers exceeds the
6 number of spreading codes, comprising:

7 receiving bandwidth allocation requests from a plurality of remote unit
8 transceivers;

9 deciding in said central unit transceiver how to allocate the available
10 bandwidth based upon the current allocation method selected from a plurality of
11 different allocation methods;

12 sending messages to said remote unit transceivers indicating which codes
13 have been assigned to them; and

14 when conditions warrant changing from the current allocation method to a
15 different allocation method, changing the current allocation method to said
16 different allocation method and thereafter making bandwidth allocation decisions
17 based upon said different allocation method.

1 57. A distributed communication system having a central unit transceiver coupled by a
2 shared transmission media to a plurality of remote unit transceivers wherein said
3 remote unit transceivers and said central unit transceiver include circuitry to

4 bidirectionally communicate digital data in synchronized frames separated by gaps using
5 any form of multiplexing and any form of modulation, and wherein said central unit
6 transceiver transmits data to said remote unit transceivers in downstream frames using
7 a single master clock and a single master carrier, both said master clock and said master
8 carrier being synthesized in said central unit transceiver from a single crystal
9 controlled oscillator, and wherein said central unit transceiver transmits a Barker code
10 signal to all remote unit transceivers during every gap between a central unit
11 transceiver frame, said Barker code having encoded therein master clock and master
12 carrier phase informaton, and wherein each said remote unit transceiver recovers said
13 master clock from said Barker code and uses said master clock signal to phase lock a local
14 clock signal and uses said phase information in said Barker code to synthesize a local
15 carrier signal in phase lock with said master carrier and uses said local clock and local
16 carrier signals to transmit data upstream to said central unit transceiver.

1 58. A method of clock recovery in a CDMA system using cyclic, orthogonal spreading
2 codes, comprising:

3 detecting the amount of crosstalk between adjacent channels spread by
4 neighboring cyclic spreading codes;

5 using the amount of crosstalk to generate a clock steering signal to alter
6 the phase of a local clock oscillator to match the phase of a clock oscillator used to
7 generate the clock used to transmit said adjacent channels.

1 59. A method of clock recovery in a distributed digital data communication system
2 having a central unit transceiver and a plurality of physically distributed remote unit
3 transceivers, comprising:

4 transmitting preamble data preceding payload data each time a remote unit
5 transceiver transitions from an inactive state to an active state;

6 using said preamble data in said central unit transceiver to determine
7 phase and amplitude error correction factors for the remote unit transceiver
8 which transmitted said preamble data;

9 using said amplitude and phase correction factors for each remote unit
10 transceiver to receive payload data from said remote unit transceiver.

1 60. A method for transmitting multiple channels of digital data simultaneously over a
2 cable television media carrying cable television programming, comprising:
3 receiving multiple channels of digital data;
4 selecting portions of said digital data from each channel and organizing
5 said portions as an information vector having n elements;
6 performing code division multiplexing by performing a matrix
7 multiplication of said information vector times a code matrix comprised of n
8 orthogonal spreading codes, each code comprising one row or one column of said
9 code matrix and having n elements, said matrix multiplication generating a result
10 vector having n elements, each element comprised of the sum of the partial
11 products of multiplication of each of the n elements of said information vector
12 times the n elements of one of said orthogonal spreading codes;
13 modulating the n elements of said result vector onto one or more radio
14 frequency carriers and transmitting the resulting radio frequency carriers on a
15 cable television media carrying cable television programming while limiting the
16 overall bandwidth of the resulting radio frequency signals so as to not interfere
17 with said cable television programming.

1 61. The process of claim 60 wherein the step of modulating the n elements of said result
2 vector onto one or more radio frequency carriers comprises the step of dividing each of
3 said n elements of said result vector into an inphase and a quadrature part, and
4 modulating the amplitude of a first radio frequency carrier during successive times
5 using the inphase parts of each of said n elements of said result vector, and modulating
6 the amplitude of a second radio frequency carrier during the same successive times using
7 the quadrature parts of each of said n elements of said result vector, said second radio
8 frequency carrier having the same frequency as said first radio frequency carrier but
9 differing in phase by 90 degrees, and summing the two resulting radio frequency
10 carriers and placing the summed signal on said cable television media.

1 62. The process of claim 60 wherein the step of performing code division multiplexing
2 includes the steps of changing the particular orthogonal code each element of each new
3 information vector is multiplied by while calculating said partial products which are
4 summed to generate the individual elements of each new result vector.

1 63 The process of claim 60 wherein the step of frequently changing the orthogonal codes
2 the elements of each new information vector are multiplied by to generate said partial
3 products which are summed to generate each element of said result vector includes the
4 steps of pseudorandomly selecting the particular orthogonal code each new information
5 vector is multiplied by to generate the partial products which are summed to generate
6 each element of each new result vector.

1 64. A method for transmitting to a central unit multiple channels of digital data
2 generated by a plurality of sources coupled to a plurality of physically distributed
3 remote units which are coupled to said central unit via a cable television media designed
4 to carry radio frequency signals, said multiple channels of digital data being transmitted
5 simultaneously over said cable television media as a plurality of frames of digital data,
6 said cable television media also carrying frequency division multiplexed cable television
7 programming, comprising:

8 establishing frame synchronization at each remote unit by determining a
9 transmit frame timing reference for each said remote unit such that, when each
10 remote unit transmits data using that remote unit's transmit frame timing
11 reference, said data will arrive at said central unit simultaneously;

12 receiving one or more channels of digital data at each remote unit;

13 at each remote unit, constructing an information vector by selecting
14 portions of said digital data from each channel of digital data received at said
15 remote unit and organizing said portions as selected elements of said information
16 vector having n elements where each element of said information vector
17 corresponds to one of said channels but wherein any element of said information
18 vector corresponding to a channel from which no data is received by any
19 particular remote unit is set to zero;

20 at each remote unit, performing code division multiplexing by performing
21 a matrix multiplication of the information vector generated at said remote unit
22 times a code matrix comprised of n orthogonal spreading codes, each code
23 comprising one row or one column of said code matrix and having n elements, said
24 matrix multiplication generating a result vector having n elements, each element
25 of said result vector comprised of the sum of the partial products of
26 multiplication of each of the n elements of said information vector times the n

27 elements of one of said orthogonal spreading codes, and wherein zero elements of
28 said information vector cause zero elements in said result vector;
29 at each remote unit, after frame synchronization has been achieved by
30 that remote unit, modulating the n elements of said result vector onto one or more
31 radio frequency carriers;
32 summing the one or more radio frequency carriers generated by each
33 remote unit with one or more radio frequency carriers generated by other remote
34 units and transmitting the resulting radio frequency carriers on a cable
35 television media carrying cable television programming while limiting the
36 overall bandwidth of the resulting radio frequency signals so as to not interfere
37 with said cable television programming.

1 65. The process of claim 64 wherein said channels of digital data received by each
2 remote unit are received in the form of a time division multiplexed data stream
3 comprised of a plurality of timeslots wherein each timeslot contains one or more data
4 bits from one channel such that all channels have a timeslot into which data from that
5 channel may be transmitted in said time division multiplexed data stream to a remote
6 unit.

1 66. The process of claim 65 wherein said step of constructing said information vector
2 comprises the steps of storing a portion of the bits from each timeslot as a corresponding
3 element of said information vector, and wherein each said frame of data transmitted from
4 each remote unit to said central unit comprises transmission of data generated from a
5 sufficient number of code division multiplexed information vectors so as to code division
6 spread all data from all timeslots to be transmitted during a single frame.

1 67. The process of claim 66 wherein each timeslot contains 9 bits, 8 of which are data
2 from any source external to said remote unit and the 9th bit of which is available to send
3 miscellaneous command and control information from the remote unit to said central
4 unit, and wherein data from three information vectors are code division multiplexed
5 from each remote unit to said central unit during each frame, and wherein each
6 information vector is constructed at a remote unit by placing 3 bits from each timeslot
7 containing data received at a remote unit into an element of said information vector, and

8 repeating this process for each of said three information vectors constructed during each
9 frame so as to transmit all 9 bits from each timeslot containing data during a frame.

1 68. A method for transmitting multiple channels of digital data over a transmission
2 media simultaneously with transmissions carrying other services in a distributed
3 communication system comprised of at least one central unit modem coupled by said
4 transmission media to a plurality of remote unit modems, comprising:

5 receiving multiple channels of digital data;

6 in each of said central unit modem and said remote unit modems composing
7 frames of data for transmission by selecting portions of said digital data from
8 each channel received by said modem and organizing said portions as an
9 information vector having n elements with at least one information vector per
10 frame;

11 in at least said remote unit modems, performing code division
12 multiplexing by performing a matrix multiplication of said information vector
13 times a code matrix comprised of n orthogonal spreading codes, each channel
14 having data therein having at least one code assigned thereto, each code
15 comprising one row or one column of said code matrix and having n elements, said
16 matrix multiplication generating a result vector having n elements;

17 using the n elements of the result vectors that comprise one frame of data
18 in said remote unit modems or, in said central unit modems, using the n elements
19 of the result vectors that define one frame of data if code division multiplexing is
20 performed or, if code division multiplexing is not performed in said central unit
21 modem, using the n elements of the information vectors that define one frame of
22 data in said central unit modem to create the information content in one or more
23 radio frequency carriers and transmitting the resulting radio frequency carriers
24 carrying the data from each remote unit frame on said transmission media toward
25 said central unit modem (hereafter referred to as the upstream channel), and
26 transmitting the resulting radio frequency carriers carrying the data from each
27 central unit frame on said transmission media toward said remote unit modems
28 (hereafter referred to as the downstream channel), while limiting the overall
29 bandwidth of the resulting radio frequency carriers transmitted in each direction
30 so as to not interfere with said other services being simultaneously transmitted
31 on said transmission media;

32 and wherein said step of composing frames of data in said central and
33 remote unit modems further comprises the steps of composing equal sized frames
34 of data in each of said central unit and remote unit modems, and wherein said step
35 of transmitting the resulting radio frequency carriers carrying the data from
36 each remote unit frame on said transmission media toward said central unit
37 modem further comprises the step of waiting for a selected transmit frame
38 timing delay for each remote unit before transmitting a frame from that remote
39 unit, and further comprising the step of performing a ranging process to
40 determine for each said remote unit modem a suitable transmit frame timing
41 delay value which will cause frames transmitted from that remote unit modem to
42 arrive at said central unit modem with frame boundaries aligned in time with the
43 frame boundaries of said central unit modem frames;

44 and further comprising the step of, prior to transmission of any frames of
45 data in the upstream direction from a remote unit modem, performing a training
46 process for the remote unit modem by performing the following steps following
47 the conclusion of said ranging process for said remote unit modem:

48 checking the accuracy of the frame synchronization established by
49 said ranging process in each remote unit modem by using a predetermined
50 one of a plurality of neighboring, orthogonal, cyclic spreading codes to
51 send training data to said central unit modem from each remote unit
52 modem, one remote unit modem at a time, and correlating said received
53 data against each of said predetermined number of orthogonal, cyclic
54 spreading codes in said central unit modem to determine how much
55 crosstalk into neighboring cyclic spreading codes exists, and, if crosstalk
56 exists for any remote unit modem, adjusting said transmit frame timing
57 delay for said remote unit modem and rechecking the accuracy of said
58 frame synchronization using the new transmit frame timing delay value,
59 and, if an acceptably small level of crosstalk exists, proceeding to the next
60 step;

61 setting the power level of transmissions from said remote unit
62 modem such that said training sequence data transmitted by said remote
63 unit modem is detected by said central unit modem with an acceptably low
64 error rate and at approximately the same power level as transmissions
65 from all the other remote unit modems;

66 performing upstream equalization by sending training sequence
67 data to said central unit modem from said remote unit modem using each of
68 a plurality of different, neighboring orthogonal, cyclic spreading codes;
69 adjusting tap weight coefficients of one or more adaptive equalizer
70 circuits in a receiver in said central unit modem to minimize detection
71 errors and reiterating for a plurality of iterations the process of sending
72 said training sequence data to said central unit modem using each of a
73 plurality of different, neighboring orthogonal spreading codes to spread
74 the spectrum of the data and again adjusting the tap weight coefficients of
75 said adaptive equalizer in said central unit modem to minimize errors,
76 and when detection errors have been minimized after a plurality of
77 iterations, sending the final tap weight coefficients for use as the tap
78 weight coefficients for an adaptive precode filter in said remote unit
79 transmitter and setting the tap weight coefficients of said adaptive
80 equalizer in said receiver of said central unit modem to one; and
81 performing downstream equalization by sending training sequence
82 data to said remote unit modem from said central unit modem using each of
83 a plurality of different, neighboring orthogonal spreading codes;
84 adjusting tap weight coefficients of a first adaptive equalizer
85 circuits in a receiver in said remote unit modem to minimize detection
86 errors and reiterating for a plurality of iterations the process of sending
87 said training sequence data from said central unit modem to said
88 unit modem using each of a plurality of different, neighboring orthogonal
89 spreading codes to spread the spectrum of the data and again adjusting the
90 tap weight coefficients of said first adaptive equalizer in said remote unit
91 modem to minimize errors, and when detection errors have been
92 minimized after a plurality of iterations, sending the final tap weight
93 coefficients for use as the tap weight coefficients for a second adaptive
94 equalizer in said receiver of said remote unit modem and setting the tap
95 weight coefficients of said first adaptive equalizer in said receiver of said
96 remote unit modem to initialization values.

1 69. The method of claim 68 wherein each remote unit and central unit frame includes a
2 gap during which no payload data is sent, and wherein said step of performing a ranging
3 process comprises the steps of:

4 1) transmitting a barker code signal from said central unit modem to said
5 remote unit modems during the gap in each central unit frame transmitted
6 downstream;

7 2) in each remote unit modem, performing said step of detecting when
8 each central unit frame arrives by detecting said barker code signal transmitted
9 by said central unit modem to establish a receive frame timing reference
10 indicating when a central unit frame has arrived;

11 3) in each remote unit modem which is performing said ranging process,
12 setting a trial and error value for said transmit frame timing delay value, and
13 imposing said transmit frame timing delay between the time of arrival of said
14 barker code signal from said central unit modem at said remote unit modem and
15 transmission of an RU ranging signal back toward said central unit modem from
16 said remote unit modem, said transmission of said RU ranging signal occurring
17 during a gap in an RU frame of said remote unit which is transmitting said remote
18 unit ranging signal, said RU ranging signal being common to all remote unit
19 modems;

20 4) in said central unit modem, monitoring each central unit frame gap for
21 the receipt of RU ranging signal, and generating a management and control data
22 message for transmission to said remote unit modems indicating whether any RU
23 ranging signal was received during a central unit frame gap;

24 5) in each remote unit modem which is performing said ranging process,
25 receiving said management and control message and determining whether an RU
26 ranging signal arrived at said central unit modem during a central unit frame
27 gap, and, if not, setting a new value for said transmit frame timing delay and
28 repeating steps 1) through 5);

29 6) repeating steps 1) through 6) until said RU ranging signal arrives
30 during a central unit frame gap, and generating and transmitting to said remote
31 units a management and control message indicating that at least one RU ranging
32 signal arrived at said central unit modem in a gap in a central unit frame and
33 requesting all remote unit modems which are performing ranging to send their
34 authentication sequences;

35 7) transmitting from each remote unit which has transmitted an RU
36 ranging pulse an authentication sequence comprised of transmission of $m/2$ RU
37 ranging signals uniquely spread among m RU frame gaps where m is an even
38 number;

39 8) monitoring said central unit frame gaps to determine if more than $m/2$
40 RU ranging signals arrived during m central unit frames following said request to
41 send authentication sequences;

42 9) if only $m/2$ RU ranging signals arrived, identifying said remote unit
43 modem which transmitted said $m/2$ ranging signals by examining the sequence of
44 said $m/2$ RU ranging signals within the m central unit frame gaps within which
45 they arrived and transmitting an ID management and control message indicating
46 the identity so determined;

47 10) in each remote unit modem which is performing said ranging
48 process, examining said management and control message to determine if said
49 remote unit modem's identity is in said management and control message;

50 11) fine tuning said transmit frame timing delay of said remote unit
51 modem the identity of which is included in said ID management and control
52 message so that said RU ranging signals transmitted by said remote unit modem
53 arrive in the center of said central unit frame gaps;

54 12) if in step 8 said central unit modem determines that more than $m/2$
55 RU ranging signals arrived, generating and transmitting to all remote units a
56 management and control message requesting all remote unit modems which are
57 carrying out said ranging process to execute collision resolution processes;

58 13) in each remote unit modem executing said collision resolution
59 protocol, executing a random yes/no decision regarding whether to continue said
60 ranging process;

61 14) retransmitting from each remote unit modem which has decided to
62 continue said ranging process the authentication sequence unique to said remote
63 unit modem;

64 15) monitoring said central unit frame gaps to determine if more than
65 $m/2$ RU ranging signals arrived during central unit frame gaps that span the
66 authentication sequence frames transmitted by the remote unit modems which are
67 still ranging;

68 16) if more than $m/2$ ranging signals are found, generating and
69 transmitting to said remote unit modems a management and control message so
70 indicating and repeating steps 13) through 15) until only $m/2$ RU ranging
71 signals are found in central unit frame gaps spanning said authentication sequence
72 interval or no RU ranging signals are found in said central unit frame gaps
73 spanning said authentication sequence interval;

74 17) if in step 15) or 16) only $m/2$ RU ranging signals are found in said
75 central unit frame gaps spanning said authentication sequence interval,
76 identifying the remote unit modem having its RU ranging signals in the central
77 unit frame gaps spanning said authentication sequence interval and fine tuning the
78 transmit frame timing delay thereof so that said RU ranging signals arrive in the
79 centers of said central unit frame gaps;

80 18) if in step 15) or 16) no RU ranging signals are found in said central
81 unit frame gaps spanning said authentication sequence interval, generating and
82 transmitting a management and control message to all remote unit modems that
83 were performing said ranging process to re-execution their collision resolution
84 processes;

85 19) in all remote unit modems that were performing said ranging process
86 and said central unit modem, repeating steps 13) through 19) until only $m/2$ RU
87 ranging signals are found in the central unit frame gaps spanning said
88 authentication sequence interval, or more than a predetermined number of
89 iterations through steps 13) through 19) have been performed;

90 20) if more than said predetermined number of iterations through steps
91 13) through 19) have been performed, repeating steps 1) through 20) until
92 only one remote unit modem's authentication sequence is found in the central unit
93 frame gaps, and that remote unit's transmit frame timing delay has been fine
94 tuned;

95 21) repeating steps 1) through 20) until all remote unit modems which
96 need to perform said ranging process have successfully concluded said ranging
97 process and have had their transmit frame timing delays fine tuned.

1 70. A bidirectional digital data communication system having a central unit transceiver
2 coupled by a transmission media to a plurality of distributed remote unit transceivers
3 wherein said central unit transceiver includes a transmitter having an encoder for

receiving data and encoding it into frame for multiplexing, a multiplexer for multiplexing the encoding data to generate multiplexed data and a modulator for using said multiplexed data to modulate one or more RF carriers so as to send downstream data to said remote unit transceivers wherein said multiplexer uses any form of multiplexing to keep data directed to different remote units separate, and wherein each said remote unit transceiver sends upstream data to said central unit transceiver using synchronous time division multiple access multiplexing using an encoder to receive upstream data and divide it into groups suitable for transmission in timeslots of an upstream frame, said upstream frame being of the same size as said downstream frames, and a time division multiple access multiplexer for receiving said smaller groups of data from said encoder and placing said groups of data into timeslots in an upstream frame assigned to this remote unit transceiver and a modulator to receive the TDMA multiplexed data and modulate it onto one or more RF carriers, each said remote unit transceiver including a frame detector circuit to recognize a marker signal in each downstream frame to establish a receive frame timing reference, and a ranging circuit for cooperating with said central unit transceiver and said frame detector circuit to establish a delay T_d relative to said receive frame timing reference for each frame and for transmitting each said upstream frame at a time T_d after receipt of said marker signal marking receipt of a downstream frame, said ranging circuit in each remote unit transceiver cooperating with said central unit transceiver to establish the value for T_d in each remote unit transceiver at a value which will cause all upstream frames from all remote unit transceivers to arrive at said central unit transceiver having their frame boundaries exactly aligned in time with the frame boundaries of said central unit frames.

71. An apparatus for transmitting multiple channels of digital data encoding supplemental services from a remote unit to a central unit over a shared transmission media using synchronous code division multiple access transmission, comprising:

means for accepting incoming data of a time division multiple access stream comprised of N time slots or channels each of which contains one or more bits of digital data encoding said supplemental services and organizing the data of said N channels into a frame comprised of M contiguous information vectors from each of which a symbol for transmission will be generated and a guardband during which no data from said time division multiple access stream is transmitted, said reorganizing carried out by reorganizing a portion of the data from each of said N channels into elements of each of

11 said M information vectors each comprised of N elements, each element comprising a
12 subgroup of bits from one channel or timeslot of said time division multiple access
13 stream plus error detection and correction bits generated by a Trellis encoder, each
14 information vector containing at least one element from each said channel plus error
15 detection and corrections bits, and for dividing each element of each said information
16 vector into a real and imaginary component;

17 means for direct sequence spread spectrum encoding of each of said M information
18 vectors using N orthogonal, cyclic codes by matrix multiplying both the real and
19 imaginary components of each information vector times a matrix embodying said N
20 orthogonal, cyclic codes such that the data from each channel is multiplied by an
21 orthogonal, cyclic spreading code assigned to that channel so as to generate M result
22 vectors, each result vector being the basis for one symbol, each result vector having N
23 elements, each element of each result vector having real and imaginary components and
24 passing the data of said real and imaginary result vectors for each frame through shaping
25 passband filters having transfer functions which satisfy the Nyquist criteria and which
26 are orthogonal to each other in the frequency domain by a Hilbert transform relationship
27 and which have bandwidths which limit the resulting intermediate frequency signals
28 exiting said filters to a predetermined bandwidth and for summing the resulting data
29 encoding intermediate frequency signals to generate M symbols for transmission, and
30 converting the data encoding said M symbols into an analog signal of said intermediate
31 frequency and for converting said intermediate frequency signal encoding said M symbols
32 to a radio frequency signal which will not interfere with other services being carried on
33 said transmission media, the resulting radio frequency signal being M-ary QAM
34 modulated, and for transmitting said modulated radio frequency carrier signals over said
35 shared transmission media said composition of said information vectors and said encoding
36 of said information vectors using orthogonal codes being such that the temporal
37 relationships of the data bits in said time division multiple access stream is altered in
38 said symbols, and such that when modulated radio frequency carrier is transmitted over
39 said shared transmission media, the energy distribution of the signals resulting from
40 said data from said N channels is spread out over substantially all of said frame and all of
41 the bandwidth of the band of frequencies devoted to said supplemental services; and

42 means for adjusting the timing of said transmission of each frame from said
43 remote unit to said central unit such that each transmitted frame arrives at said central
44 unit aligned in time with frame boundaries of frames of said central unit.

1 72. A head end modem for providing multiple-user, multiple-source simultaneous
2 digital communication over a limited bandwidth with one or more remote unit modems in
3 a distributed systems linked by a transmission medium, comprising:

4 a framing/addressing/packetizing circuit for receiving payload data
5 bytes and organizing said payload data into frames and organizing said payload data
6 such that information as to which remote unit modem and peripheral each payload
7 data byte is directed can be determined;

8 a master clock for generating a master clock signal;

9 a master carrier local oscillator for generating one or more carrier
10 signals which will be modulated with digital data to be transmitted;

11 a transmitter for receiving said data from said
12 framing/addressing/packetizing circuit and said master clock signal and said one
13 or more carrier signals and using said data to modulate said one or more carrier
14 signals using any modulation process which can also transmit said master clock
15 reference signal and said carrier signals to said remote unit modems for use
16 there for synchronization including synchronization to said frame boundaries,
17 said transmitter coupled to said transmission media so as to output said one or
18 more modulated carrier signals as downstream radio frequency signals; and

19 an SCDMA receiver coupled to receive upstream RF signals with digital
20 data by said remote unit modems and coupled to said master clock and said master
21 carrier local oscillator to receive said master clock signal and said master clock
22 local oscillator, said SCDMA receiver functioning to synchronously extract
23 payload data from said upstream RF signals by performing the inverse code
24 transformation of a code transformation which was performed by an SCDMA
25 transmitter in a remote unit modem which modulated said upstream RF signals by
26 spreading the spectrum thereof using orthogonal, pseudorandom spreading codes
27 assigned to that modem, said inverse code transformation performed on signals
28 received from a particular remote unit modem using the same orthogonal
29 spreading codes used by said remote unit modem, said extracted payload data being
30 presented at an output;

31 a gap monitor circuit coupled to said SCDMA receiver for aiding the
32 process of achieving frame synchronization by said remote unit modems by
33 monitoring an interval during each frame for the presence of unique codes

34 transmitted by said remote unit modems and for generating status data indicating
35 how many codes have been received during said interval;

36 a circuit for receiving said status data from said gap monitor circuit and
37 generating suitable management and control data needed by the remote units to
38 achieve frame synchronization such that all frames of like number transmitted
39 by the various remote unit modems arrive at said central unit modem at the same
40 time; and

41 a data transfer circuit for receiving said management and control data and
42 causing said transmitter to transmit same during an interval dedicated to
43 transmission of said management and control data.

1 73. A remote unit modem for providing multiple-user, multiple-source simultaneous
2 digital communication over a limited bandwidth with a central unit modem in a
3 distributed system linked by a transmission medium, comprising:

4 a receiver coupled to receive downstream radio frequency signals
5 organized into frames from said central unit, said receiver functioning to
6 synchronously extract payload data for use by peripheral devices or processes
7 coupled to said remote unit modem and synchronously extract any management
8 and control data transmitted by the CU to said said remote unit modem to achieve
9 frame synchronization or in support of other management function, and further
10 functioning to recover master clock and carrier reference signals transmitted by
11 said central unit modem, and wherein said central unit modem organizes data sent
12 to said remote unit modem into frames each of which has a gap therein during
13 which no payload data is sent, said central unit modem transmitting a barker code
14 during at least one said gap, said receiver further functioning to detect when said
15 barker code transmitted by said central unit modem during a gap is received and
16 generating a receive frame timing reference signal establishing a receive frame
17 timing reference as to when the frames of data transmitted by said central unit
18 modem start, said receiver including at least a gap monitor circuit, a
19 demodulator, a detector, and, if necessary a decoder/despreader circuit which are
20 compatible with the central unit transmitter such that said receiver is capable of
21 performing said extraction of payload and management and control data and
22 detecting said barker code;

an SCDMA transmitter coupled to receive said master clock and carrier reference signals recovered by said receiver, and coupled to receive payload data from said peripheral devices or processes coupled to said remote unit modem, and coupled to receive management and control data to be transmitted to said central unit modem, said SCDMA transmitter functioning to organize said payload data and said management and control data into frames of the same size as the frames of data transmitted to said receiver by said central unit modem and to spread the Fourier spectrum of said payload data and said management and control data over a bandwidth which is much greater than the Fourier spectrum said payload data and said management and control data originally had, and further functioning to use said spread spectrum data to modulate one or more carrier signals for transmission on said transmission media, said process of organizing payload and management and control data into frames, spreading the spectrum of said data and using said spread spectrum data to modulate one or more carriers being done synchronously using said master clock and carrier reference signals recovered by said receiver, said transmitter also functioning to transmit each frame of modulated signals to said central unit to said central unit modem over said transmission media a predetermined transmit frame timing delay after a frame of data has been received from said central unit modem, as established by said receive frame timing reference signal;

a ranging generator circuit functioning to generate and send to said SCDMA transmitter data defining a barker code for transmission to said central unit modem during a ranging process;

a control circuit coupled to receive said management and control data extracted by said receiver and said receive frame timing reference signal generated by said receiver and for controlling said SCDMA transmitter to carry out a ranging process by calculating a trial and error value for said transmit frame timing delay T_d and sending T_d to said SCDMA transmitter to control the time of transmission of a barker code, said control circuit also for monitoring said management and control data to determine if the barker code arrived at said central unit modem during a gap, and for continuing to vary the value of T_d until said barker codes transmitted by said SCDMA transmitter arrive in said gap as indicated by said management and control data thereby achieving frame synchronization and thereafter holding the value of T_d steady.

1 74. A transmitter apparatus for simultaneously transmitting to a receiver multiple
2 channels of digital data over a cable television media carrying cable television
3 programming, comprising:

4 a framer circuit for receiving a time division multiplexed stream of data
5 comprised of N timeslots per frame, each timeslot carrying digital data from one
6 of N channels, said framer for storing in a memory the data from selected ones of
7 said timeslots assigned to said transmitter, and for generating an information
8 vector having N elements corresponding to said N timeslots, predetermined ones
9 of said information vector elements corresponding to said selected timeslots
10 assigned to said transmitter from which data was stored by said framer circuit,
11 each of said predetermined elements of said information vector corresponding to
12 timeslots assigned to said transmitter comprised of a plurality of bits which
13 constitute a fraction of the data of one of said timeslots assigned to said
14 transmitter;

15 a convolutional encoder for selectively adding one or more redundant bits
16 to each element of said information vector to implement trellis modulation to
17 generate a new information vector;

18 a code division multiplexer circuit for matrix multiplying said new
19 information vector times a code matrix comprised of N mathematically orthogonal
20 codes, each row comprised of an orthogonal code having N elements to generate a
21 result vector having N elements;

22 a modulator for using each element of said result vector to quadrature
23 amplitude modulate two radio frequency carriers having the same frequency but
24 separated in phase by 90 degrees to generate inphase and quadrature RF signals,
25 said modulation being achieved by dividing the bits of each element of said result
26 vector into first and second parts and using the number represented by each part
27 to define the amplitude of said inphase and quadrature RF signals, respectively,
28 and summing said inphase and quadrature RF signals prior to transmission on
29 said cable television media;

30 means for achieving frame synchronization between frames transmitted
31 by said transmitter apparatus and the frame boundaries of frames within said
32 receiver.

1 75. The apparatus of claim 74 further comprising a scrambler circuit coupled to
2 receive elements of said information vector from said framer circuit, pseudorandomly
3 scramble the bits of each element thereof to generate a scrambled information vector,
4 and transmit said scrambled information vector to said convolutional encoder and
5 wherein said convolutional encoder encodes the elements of said scrambled information
6 vector with redundant bits.

1 76. The apparatus of claim 75 wherein said convolutional encoder has an idle mode
2 wherein only zeroes are added as redundant bits, a normal mode wherein a first selected
3 number of redundant bits are added to each element of the information vector based upon
4 the data selected from the same timeslot of an earlier time to generate the same element
5 of a previous information vector, and a fallback mode wherein a number of redundant
6 bits larger than said first selected number of redundant bits are added to each element of
7 said information vector to generate said new information vector, the mode in which said
8 convolutional encoder operates being selectable by manipulation of a mode control signal
9 transmitted to a mode control input of said convolutional encoder.

1 77. The apparatus of claim 76 further comprising code diversity means coupled to said
2 framer circuit for controlling the order in which said information vector elements are
3 read from said framer circuit and input to said scrambler circuit, and further
4 comprising a buffer memory for storing said scrambled information vector, said code
5 diversity means controlling the locations in said buffer memory in which is stored each
6 scrambled element of said scrambled information vector.

1 78. The apparatus of claim 75 further comprising a precode filter coupled to receive at
2 least said elements of said result vector and to perform an equalization process thereon
3 to predistort said result vector elements prior to transmission to generate predistorted
4 result vector elements and wherein said modulator uses said predistorted result vector
5 elements to generate said inphase and quadrature RF signals such that said inphase and
6 quadrature RF signals arrive at said receiver with substantially less distortion caused
7 by impairments encountered in propagating along said cable television medium, said
8 precode filter having an input for receiving a coefficient signal which controls the
9 characteristics of the predistortion function applied to the elements of said result
10 vector.

1 79. The apparatus of claim 78 wherein said coefficient signal is set so as to establish
2 said characteristics of said predistortion function based upon the position of the
3 transmitter on said cable television media and the impairments then existing which will
4 affect signals transmitted from a transmitter at that position.

1 80. The apparatus of claim 75 further comprising a shaping filter coupled to receive
2 said scaled result vector elements before they are supplied to said analog to digital
3 converter, said shaping filter having a raised cosine transfer function suitable to limit
4 the bandwidth of the combined RF signal generated by summing said inphase and
5 quadrature RF signals and suitable to satisfy the Nyquist criteria so as to optimize
6 signal-to-noise ratio and minimize interference with signals from other transmitters
7 coupled to said cable television media.

1 81. The apparatus of claim 75 wherein each timeslot contains 8 bits of data to which a
2 9th bit is added, said 9th bit encoded with predetermined nonpayload information, and
3 wherein said framer circuit stores all 9 bits from timeslots assigned to it in memory
4 locations in memory, and wherein data is read out from said framer circuit in frames,
5 each frame comprised of three symbols, each symbol having N elements corresponding to
6 the N elements of an information vector, and wherein, during each frame, said framer
7 circuit outputs three sequential information vectors from which the three sequential
8 symbols of the frame will be generated, the elements of each of said three sequential
9 information vectors each corresponding to a timeslot currently assigned to said
10 transmitter, each said element containing three of the nine bits from the corresponding
11 assigned timeslot, said three bits hereafter called a tribit, and wherein said
12 convolutional encoder, when operating in normal mode, adds a 4th redundant bit to each
13 tribit to generate the elements of said new information vector prior to said matrix
14 multiplication carried out by said code division multiplexer circuit on said new
15 information vector.

1 82. The apparatus of claim 75 wherein said code division multiplexer circuit generates
2 each of said N mathematically orthogonal codes from a cyclic code and is structured to
3 perform said matrix multiplication by generating one orthogonal code, multiply each
4 code element of the code so generated by a corresponding element of said new information

vector, and sum the partial products to generate an element of said result vector and then generate the next orthogonal code from the cyclic code and repeat the process to generate the next element of said result vector.

83. A system for bidirectional communication of digital data comprising:

a central unit comprising a code division multiple access transmitter and a code division multiple access receiver;

a transmission media coupled to said central unit transmitter and receiver;

a plurality of physically distributed remote units coupled to said central unit by said transmission media, each remote unit having a code division multiple access transmitter and a code division multiple access receiver;

and wherein said central unit transmitter includes means for assigning each remote unit one or more codes from a set of orthogonal codes and wherein each said remote unit transmitter and said central unit transmitter include means for using said orthogonal codes assigned to that remote unit to encode all payload data intended for exchange between said remote unit and said central unit;

and wherein each said transmitter includes a modulator to use said digital data, after encoding using said orthogonal codes, to modulate a radio frequency carrier to generate modulated RF signals for transmission on said transmission media;

and wherein said transmitters in said central unit and said remote units are structured to transmit said modulated RF signals in frames, each frame defined as one or more symbols comprising encoded payload data and a guardband during which no payload data is transmitted, each frame separated from adjacent frames by said guardband;

and wherein central unit transmitter includes a circuit to transmit a barker code during each frame;

and wherein each remote unit transmitter includes means for carrying out a trial and error process of adjusting a transmit frame timing delay and transmitting said barker code back toward said central unit, hereafter referred to as the ranging process, and wherein each central unit receiver includes means for monitoring each guardband to determine when a barker code transmitted by a single remote unit transmitter has arrived during said guardband or if multiple

barker codes have arrived, and wherein said central unit transmitter is coupled to said central unit receiver and receives status information therefrom regarding whether a single or multiple barker codes have been received within a guardband and transmits said status information to said remote units, and wherein each remote unit receiver includes means for monitoring said status information transmitted from said central unit and for receiving information from said remote unit transmitter regarding whether said remote unit transmitter is currently carrying out said ranging process, and, when said status information received from said central unit indicates only a single barker code was received during said guardband and information from said remote unit transmitter indicates that remote unit is currently carrying out said ranging process, said remote unit receiver controls said remote unit transmitter to transmit an identification code unique to only that remote unit, and wherein said central unit receiver includes means to determine what identification code was received and to control said central unit transmitter to transmit the received identification code back to all remote units, and wherein said remote unit receivers includes means for comparing the identification code transmitted by said central unit to the identification code of said remote unit, and, if there is a match, for controlling said remote unit transmitter to set said transmit frame timing delay at the delay value which resulted in said barker code arriving at said central unit during said guardband.